

# INCUBATOR SHAKER SHA026-311B



# INCUBATOR SHAKER SHA026-311B

## SHA026-311B INCUBATOR SHAKER

Large LCD screen to display more data at same time

R134a refrigerant, imported compressor and fan motor

Big observation windows

304 Stainless steel chamber and platform, easy to clean

The parameters can be automatically stored in case of power failure, and it will continue run as presetting program after turn on

Microprocessor PID controller for temperature and shaking speed with timing function



## SPECIFICATIONS

Model	SHA026-311B
Speed Range	40-300 rpm
Electrical Requirement	220 V 50 Hz
Amplitude	26 mm
Display Resolution	0.1°C
Power Consumption	1300 W
Platform Dimensions	920x500 mm
External Dimension	1250Wx660Dx915H mm
Timing range	0~5999 min

# LABSTAC

**Labstac LLC**

82 Wendell Avenue, STE 100, Pittsfield, MA, 01201, USA

Email: [contact@mail.labstac.com](mailto:contact@mail.labstac.com) | Website: [labstac.com](http://labstac.com)